Control using free SeraNova app



Q





Step by Step:

1.Download and launch the SeraNova app https://play.google.com/store/apps/details?id=com.seranova.cloud

or use the browser version of SeraNova at at https://seranova.eu/login



Scan a QR code with your Android Phone





Register and create a new account or Log in with your user name and password

If You don't know IMEI

Send SMS to the module: INST00000 100 1

• You will receive SMS with IMEI

Or connect the module to the computer via miniUSB cable Install configuration software SERA2 (<u>https://www.topkodas.lt/downloads/</u>) Go to SERA2> System Options> System Info

③ SERA2 [PROGATE]							
📄 File 🔌 Settings 🛛 🚑 Dev	ices 🛛 🐺 Read [F5]	🞇 Write [F6] 🛛 🛑 Update 🛭 🔞 Help					
System Options	System						
GSM Communications	General System Options System Fault/Troubles System Info						
Inputs/Burgiar Alarm Zones Outputs (PGM)	GSM Modem:	2G GSM/GPRS/EDGE Quad band (850/900/1800/1900MHz)					
- Automation/Sensors	Hardware:	PROGATE					
Event Summary	Bootloader:	PROGATE 2G boot v2					
Events Log							
···· RT Testing&Monitoring	Firmware:	042105092056					
ⁱ Firmware	Serial No:	00000091					
	IMEI:	8693(
~ ~	Modern Type:	2G-QB / V01					



• Go to SY	STEMS	, pres	ss "Add	New S	System"
च ം% ноте	Security GTCOM2 -		-	press	Save
🛋 Add New Sys	tem	×			
System Name		0 (100			
Cevice UID/IMEI/	MAC *				
App Key *	12345	6 📎	-		
Object Address		0 / 6			
User Access Cod	e 1234	0 / 100			
	1201	0 / 6			
Phone Numer					
	SAVE				



1. Select the system

•-ိုင္ရွိ Gate	→
SYSTEM	°-ဝို့ SYSTEMS
stem	
Q	. : : :::::::::::::::::::::::::::::::::
vstem	RSSI
ome Security TCOM2 uno r., LT-54311, Lithuanta	77%
ate	 87%
Records per page:	50 💌 1-2 of 2
	SYSTEM

2. Go to SYSTEM



1. ADD WIDGET> PGM Outputs> OUT1



2. Select the icon, pulse or level, etc.



3. Add to Dashboard



• Go to DASHBOARD

≡	ႋ်ိုင္ရွိ Gate	▼ Zivile ▼	=
DASHBOARD	SYSTEM	∘-ဝို္င္ရွိ SYSTEMS	DASHBOA
Gate	PGM1		Gate

=	•ဝိုင်္ပိ Gate	►ئکئ Zivile ◄
DASHBOARD	SYSTEM	°-ဝို SYSTEMS
Gate	PGM1	

• The first person to add a system becomes an administrator. He can add other users and give them permissions : admin or user

00)	වුසු Zivile 👻	🚍 ေလြွိ Gate 👻	ව _{ුබු} Zivile ╺		ంచ్రి Gate 👻 లైస్రి Zivile 👻
SERA NOVA	o-Òζ̈́ SYSTEMS	Add New User		Add New User	×
 ☆ Gate ▲ Zivile ☑ zivile@topkodas.lt 	PGM1	Search Q	:: 🎟	Email Address info@topkodas.lt	
\Diamond	BBB	Name Phone	Action		16 / 100
Dashboard		+370623	<u>2</u>	User Name Aidas	
Inputs / Zones		Master	1-1 of 1	Phone Numer	5 / 31
Outputs				+ 37065558449	2
Sensors / Thermostats		Export to csv		User Code 1111	
Events				iButton Code	
				QWERT	YUIOP
	nts			ASDF	GHJKL

IMPORTANT:

- When adding the controller to SeraNova app:
- 1. The SERA Cloud service must be turned on

in SERA2> GSM Communication> SERA Cloud Service

2.The power supply must be turned on ("PWR" LED must blink green);

3.Must be registered in to network ("REG" LED must be solid yellow).



More information:

- https://www.topkodas.lt/downloads/
- info@topkodas.lt